

HIGH SPEED SIGNAL			
P1(4x-Pluggable-QSFP)		P2(4x-Pluggable-QSFP)	
PAD	SIGNAL	PAD	SIGNAL
02	TX2n	21	RX2n
03	TX2p	22	RX2p
05	TX4n	24	RX4n
06	TX4p	25	RX4p
14	RX3p	33	TX3p
15	RX3n	34	TX3n
17	RX1p	36	TX1p
18	RX1n	37	TX1n
21	RX2n	02	TX2n
22	RX2p	03	TX2p
24	RX4n	05	TX4n
25	RX4p	06	TX4p
33	TX3p	14	RX3p
34	TX3n	15	RX3n
36	TX1p	17	RX1p
37	TX1n	18	RX1n
GND GROUP	GND	GND GROUP	GND
GND GROUP 01,04,07,13,16,19 20,23,26,32,35,38		GND GROUP 01,04,07,13,16,19 20,23,26,32,35,38	

LOW SPEED SIGNAL & POWER		P1(4x-Pluggable-QSFP)	
PAD	SIGNAL	PAD	SIGNAL
08	ModSelL		
09	ResetL		
10	VccRx		
11	SCL		
12	SDA		
27	ModPrsL		
28	IntL		
29	VccTx		
30	Vcc1		
31	LPMode		

N.C.   
 SERIAL EEPROM   
 Vcc   
 GND

LOW SPEED SIGNAL & POWER		P2(4x-Pluggable-QSFP)	
PAD	SIGNAL	PAD	SIGNAL
08	ModSelL		
09	ResetL		
10	VccRx		
11	SCL		
12	SDA		
27	ModPrsL		
28	IntL		
29	VccTx		
30	Vcc1		
31	LPMode		

N.C.   
 SERIAL EEPROM   
 Vcc   
 GND



**P/N: QSFP - QSFP - XX**

**Desc. : QSFP - QSFP cable**

Drawings are property of Serial Cables, LLC and for information purposes only. Do Not Edit or Copy